

5406 Prime Factors

Webster defines *prime* as:

prime (*prīm*) *n.* [ME, fr. MF, fem. of *prin* first, L *primus*; akin to L *prior*] **1:** first in time: **original** **2 a:** having no factor except itself and one (3 is a \sim number) **b:** having no common factor except one (12 and 25 are relatively \sim) **3 a:** first in rank, authority or significance: **principal** **b:** having the highest quality or value (\sim television time) [from *Webster's New Collegiate Dictionary*]

The most relevant definition for this problem is 2a: An integer $g > 1$ is said to be *prime* if and only if its only positive divisors are itself and one (otherwise it is said to be *composite*). For example, the number 21 is composite; the number 23 is prime. Note that the decomposition of a positive number g into its prime factors, i.e.,

$$g = f_1 \times f_2 \times \cdots \times f_n$$

is unique if we assert that $f_i > 1$ for all i and $f_i \leq f_j$ for $i < j$.

One interesting class of prime numbers are the so-called *Mersenne* primes which are of the form $2^p - 1$. Euler proved that $2^{31} - 1$ is prime in 1772 — all without the aid of a computer.

Input

The input will consist of a sequence of numbers. Each line of input will contain one number g in the range $-2^{31} < g < 2^{31}$, but different of -1 and 1. The end of input will be indicated by an input line having a value of zero.

Output

For each line of input, your program should print a line of output consisting of the input number and its prime factors. For an input number $g > 0$, $g = f_1 \times f_2 \times \cdots \times f_n$, where each f_i is a prime number greater than unity (with $f_i \leq f_j$ for $i < j$), the format of the output line should be

$$g = f_1 \times f_2 \times \cdots \times f_n$$

When $g < 0$, if $|g| = f_1 \times f_2 \times \cdots \times f_n$, the format of the output line should be

$$g = -1 \times f_1 \times f_2 \times \cdots \times f_n$$

Sample Input

```
-190
-191
-192
-193
-194
195
196
197
198
199
200
0
```

Sample Output

$$-190 = -1 \times 2 \times 5 \times 19$$

$$-191 = -1 \times 191$$

$$-192 = -1 \times 2 \times 2 \times 2 \times 2 \times 2 \times 2 \times 2 \times 3$$

$$-193 = -1 \times 193$$

$$-194 = -1 \times 2 \times 97$$

$$195 = 3 \times 5 \times 13$$

$$196 = 2 \times 2 \times 7 \times 7$$

$$197 = 197$$

$$198 = 2 \times 3 \times 3 \times 11$$

$$199 = 199$$

$$200 = 2 \times 2 \times 2 \times 5 \times 5$$